



Description

Mounts to building framing, and is designed as a mounting plate to which Heatizon Control Units and Transformers will be attached.

Heatizon Systems Rough-In Kit contains the following:

- 12" h X 17" w mounting Back Plate (P1320)
- 50' Thermostat Wire (M316)
- 50' to 200' Cold Lead (E210)
- Installation Manual
- 5 Plastic Conductor Bushing (M391)
- 4 Mounting Screws



Each Rough-In Kit contains enough Cold Lead to extend the total vertical and horizontal distance between the Control Unit/Transformer location and the area where the heating element will begin and end. If backplate is to be mounted to concrete use in conjunction with a Heatizon Rough - Box (Part # P4184)

Uses

Heatizon Rough-In Kit is used for mounting:

- 1- CBX6, CBX6T, CBX23, CBX23T, CBX7, Radiant 8 Control Unit (Note: SLC 500 Control Unit does not require a Rough-In Kit);

and

- 1- S050, S101, S102, S103, S104, S105, S106, S202, or S203 Transformer



Note: Additional Cold Lead (Heatizon Part Number E210) is available from Heatizon Systems.

Available Sizes

Rough-in Kits are sized according to the total length of the Cold Lead. Rough-in Kits offered by Heatizon Systems include:

- Rough-In Kit 50
- Rough-In Kit 100
- Rough-In Kit 150
- Rough-In Kit 200

